



DES-1008D

DES-1008D switch provides 8 auto-sensing 10/100Mbps ports in a palm-sized box. The switch allows mix and match of Ethernet and Fast Ethernet in full- and half-duplex modes.

8-Port 10/100Mbps Switch for SOHO

The DES-1008D is an unmanaged 10/100Mbps switch designed to enhance small workgroup performance while providing a high level of flexibility. Powerful yet easy to use, this device allows users to simply plug any port to either a 10Mbps or 100Mbps network to multiply bandwidths, boost response time and satisfy heavy load demands.

8 Auto-sensing 10/100Mbps Ports

The switch comes with 8 10/100Mbps ports, allowing a small workgroup to flexibly connect to Ethernet and Fast Ethernet and integrate. These intelligent ports detect the network speed and auto-negotiate between 100BASE-TX and 10BASE-T, as well as between full- and half-duplex.

Flow Control for Secure Transmission

All ports support 802.3x flow control. This function minimizes dropped packets by sending out collision signals when the port's receiving buffer is full. Flow control is available in the full-duplex mode.

Auto-negotiation of MDI/MDIX Cross Over

All ports support auto-negotiation of MDI/MDIX cross over. This eliminates the need for cross over cables or uplink ports. Any port can simply plug to a server, a hub or a switch, using the usual straight-through twisted-pair cable.

SOHO Plug-and-Play

With 8 plug-and-play ports, the switch is a perfect choice for the small workgroup to upgrade performance in a client/server environment. The ports can be connected to servers in full-duplex, or hubs in half-duplex.

Desktop Power

With low-cost connection per-port, the switch can also be set up for direct connection from the PCs. This relieves data bottleneck by giving each workstation a dedicated bandwidth on the network.

Key Features

- 8 10/100Mbps ports
- Per-port auto MDI/MDIX
- All ports support full/half-duplex, network speed auto-negotiation
- Per-port 802.3x flow control for protection against data loss
- Auto-learning of network configuration
- Secure store-and-forward switching scheme
- Auto-correction of reverse twisted-pair polarity
- Compact size

DES-1008D

Technical Specifications

10/100Mbps Unmanaged Switch

General

Standards

- IEEE 802.3 10BASE-T Ethernet
- IEEE 802.3u 100BASE-TX Fast Ethernet
- ANSI/IEEE 802.3 NWay auto-negotiation
- IEEE 802.3x Flow Control

Protocol

CSMA/CD

Data Transfer Rates

- Ethernet:
 - 10Mbps (half-duplex)
 - 20Mbps (full-duplex)
- Fast Ethernet:
 - 100Mbps (half-duplex)
 - 200Mbps (full-duplex)

Topology

Star

Network Cables

- 10BASE-T:
 - UTP Cat. 3, 4, 5 (100 m)
 - EIA/TIA-568 STP (100 m)
- 100BASE-TX:
 - UTP Cat. 5 (100 m)
 - EIA/TIA-5681 STP (100 m)

Number of Ports

10/100Mbps port x 8

Twisted-pair Rx Reverse Polarity

Auto-correction

LED Report

Per device:

- Power

Per port:

- 10Mbps, 100Mbps
- Full-duplex, Collision

Performance

Transmission Method

Store-and-forward

MAC Address Table

8K entries per device

MAC Address Learning

Automatic update

Buffer Memory

256Kbytes per device

Packet Filtering Rates

- 10BASE-T: 14,880 pps per port (half-duplex)
- 100BASE-TX: 148,800 pps per port (half-duplex)

Packet Forwarding Rates

- 10BASE-T: 14,880 pps per port (half-duplex)
- 100BASE-TX: 148,800 pps per port (half-duplex)

Physical & Environmental

Power Input

DC 7.5V/1A

Through external AC power adapter

Power Consumption

2 watts (max.)

Operating Temperature

0° - 50°C

Storage Temperature

-10° - 70°C

Operating Humidity

10% - 90%

Storage Humidity

5% - 90%

Dimensions

192 (W) x 118 (D) x 32 (H) mm

Weight

301 grams

Emission (EMI)

- FCC Class B
- CE Class A
- VCCI Class A



Ordering Information

Unmanaged Fast Ethernet Switch DES-1008D 8 10/100Mbps ports

Please specify one of the following after the model number:

/U	Includes no AC power adapter
/A	Includes a US standard AC power adapter
/E	Includes an EU standard AC power adapter
/B	Includes a UK standard AC power adapter
/N	Includes an Australia standard AC power adapter
/CN	Includes a China standard AC power adapter

D-Link®

Specifications subject to change without prior notice.
D-Link is a registered trademark of D-Link Corporation/D-Link System Inc. All other trademarks belong to their proprietors.

U.S.A.

Canada

Europe

U.K.

Germany

France

Benelux

Italy

Iberia

Sweden

Norway

Denmark

Finland

Singapore

Australia

Japan

China

India

Middle East

South America

Brasil

South Africa

Russia

Taiwan

D-Link Corp.

TEL: 1-949-788-0805

TEL: 1-905-829-5033

TEL: 44-20-8731-5555

TEL: 44-20-8731-5555

TEL: 49-61-96779900

TEL: 33-1-30238688

TEL: 31-10-204-5740

TEL: 39-02-2900-0676

TEL: 34-93-490770

TEL: 46-(0)8-564-61900

TEL: 47-22-991890

TEL: 45-43-969040

TEL: 358-9-2707-5080

TEL: 65-6774-6233

TEL: 61-2-8899-1800

TEL: 81-3-5434-9678

TEL: 86-010-8518-2533

TEL: 91-22-652-6696

TEL: 202-6244615

TEL: 56-2-232-3185

TEL: 55-11-3094-2910

TEL: 27(0)126652165

TEL: 7-095-737-3389

TEL: 886-2-2910-2626

TEL: 886-2-2916-1600

FAX: 1-949-753-7033

FAX: 1-905-829-5095

FAX: 44-20-8731-5511

FAX: 44-20-8731-5511

FAX: 49-61-967799300

FAX: 33-1-30238689

FAX: 31-10-204-5880

FAX: 39-02-2900-1723

FAX: 34-93-4910795

FAX: 46-(0)8-564-61901

FAX: 47-22-205700

FAX: 45-43-424347

FAX: 358-9-2707-5081

FAX: 65-6774-6322

FAX: 61-2-8899-1868

FAX: 81-3-5434-9868

FAX: 86-010-8518-2250

FAX: 91-22-652-8914

FAX: 202-6244583

FAX: 56-2-232-0923

FAX: 55-11-3094-2921

FAX: 27(0)126652186

FAX: 7-095-737-3390

FAX: 886-2-2910-1515

FAX: 886-2-2914-6299



RECYCLABLE
Rev. 04 (Nov. 2002)
Printed in Taiwan