



DES-1016R+
DES-1024R+

Top: DES-1016R+ switch with 16 auto-sensing 10/100Mbps ports.
Bottom: DES-1024R+ switch with 24 auto-sensing 10/100Mbps ports.
Each switch is equipped with an open slot (on the front) for you to fit in an optional 2-port 100Mbps Fast Ethernet fiber module.

10/100Mbps Switches for Workgroups

These unmanaged 10/100Mbps switches are designed to enhance workgroup performance while providing a high level of flexibility. Powerful yet easy to use, these devices allow users to simply plug any port to either a 10Mbps or 100Mbps network to multiply bandwidths, boost response time and satisfy heavy load demands.

Choices of 16 or 24 10/100Mbps Ports

Two choices of switches are available: one with 16 10/100Mbps ports, the other with 24 10/100Mbps ports. These ports detect the network speed and auto-negotiate between 100BASE-TX and 10BASE-T, as well as full- and half-duplex.

Auto-adjustment of MDI/MDIX Cross Over

All 10/100Mbps ports auto-adjust MDI/MDIX twisted-pair cable cross-over, eliminating the need for cross-over cables or uplink buttons. You simply plug any port to a server, a workstation or a hub, using the usual straight-through twisted-pair cable. The port will auto-sense the attached device type and adjust the Tx, Rx pin assignments accordingly before transmitting and receiving data.

Optional 100Mbps Fiber Ports

An open slot is provided on the front panel to let you install an optional Fast Ethernet fiber module. This module provides 2 100Mbps fiber ports for 2 server connections or switch-to-switch cascading over the reliable fiber cables, which can be up to 2km long.

Flow Control Protects Against Data Loss

Using flow control (in full duplex and applicable to all 10/100Mbps ports), the switch monitors the buffer status of each port. During peak usage, if the buffer fills to capacity, the switch detects this and signals to the attached node to delay sending new data until the switch can accept it. This operation minimizes the chance of any buffer overrun where incoming data overwrites the current data that has not been completely flushed out of the buffer. This function works with flow control supported Fast Ethernet adapters (installed in servers) connected to the switch in dedicated bandwidth configuration. It can also be applied to switch-to-switch cascading.

Easy Expansion

Cascading 2 switches together to expand the network using the twisted-pair ports is easy. As all 10/100Mbps ports support auto-negotiation of MDI/MDIX twisted-pair cable cross-over, you simply connect 2 switches together without having to find a cross-over cable or to make sure the ports are uplink ports. At 200Mbps full-duplex speed, all ports provide a fast switch-to-switch dedicated bandwidth. 16 or 24 10/100Mbps ports

Key Features

- 1 expansion slot for 2 optional 100Mbps fiber ports
- Full/half duplex support for each port
- Auto-learning of network configuration
- IEEE 802.3x flow control in full duplex mode for protection against data loss
- Back pressure in half duplex mode
- Auto-adjustment of MDI/MDIX cross over for each port
- Auto-correction of twisted-pair polarity reverse
- RAM buffer dynamically allocated for each port

DES-1016R+/1024R+

Technical Specifications

General

Standards

- IEEE 802.3 10BASE-T Ethernet
- IEEE 802.3u 100BASE-TX Fast Ethernet
- IEEE 802.3u 100BASE-FX Fast Ethernet
- ANSI/IEEE 802.3 NWay auto-negotiation
- IEEE 802.3x Flow Control

Protocol

CSMA/CD

Data Transfer Rates

- Ethernet:
 - 10Mbps (half duplex)
 - 20Mbps (full duplex)
- Fast Ethernet:
 - 100Mbps (half duplex)
 - 200Mbps (full duplex)

Topology

Star

Network Cables

- 10BASE-T:
 - 2-pair UTP Cat. 3, 4, 5 (100 m)
 - EIA/TIA-568 100-ohm STP (100 m)
- 100BASE-TX:
 - 2-pair UTP Cat. 5 (100 m)
 - EIA/TIA-568 100-ohm STP (100 m)
- 100BASE-FX:
 - Multi-mode (62.5/125 um or 50/125 um fiber cabling with SC connector)

Number of Built-in Ports

- DES-1016R+: 10/100Mbps port x 16
- DES-1024R+: 10/100Mbps port x 24
- DES-102F: 100BASE-FX port x 2

Media Interface Exchange

Auto-negotiation of MDI-II/MDI-X for all 10/100Mbps ports

Twisted-pair Rx Reverse Polarity

Auto-correction

LED Report

- Per device:
 - Power
- Per 10/100Mbps port:
 - 100Mbps speeds
 - Link/activity

Performance

Transmission Method

Store-and-forward

MAC Address Table

4K entries per device

Packet Filtering Rates

- Ethernet: 14,880 pps per port (half-duplex)
- Fast Ethernet: 148,800 pps per port (half-duplex)

Packet Forwarding Rates

- Ethernet: 14,880 pps per port (half-duplex)
- Fast Ethernet: 148,800 pps per port (half-duplex)

RAM Buffer

256KB per 8 ports

Flow Control

- IEEE 802.3x flow control per 10/100Mbps port in full duplex
- Back pressure per 10/100Mbps port in half duplex

Physical & Environmental

AC Input

100 - 240 VAC, 50/60 Hz
Internal universal power supply

Power Consumption

- DES-1016R+: 39 watts (max.)
- DES-1024R+: 39 watts (max.)

10/100Mbps Unmanaged Switches



Ventilation

- DES-1016R+: 12V - 0.09A DC fan x 1
- DES-1024R+: 12V - 0.09A DC fan x 1

Operating Temperature

0° - 50°C (32° - 122° F)

Storage Temperature

-30° - 60°C (-22° - 140° F)

Humidity

5% - 95% non-condensing

Dimensions

441 x 207 x 44 mm
(17.4 x 8.15 x 1.732 inches)
19-inch rack-mount width, 1 U height

Weight

- DES-1016R+: 2.55 kg (5.62 lb.), 2.6kg (with DES-102F module)
- DES-1024R+: 2.65 kg (5.84 lb.), 2.7 kg (with DES-102F module)

Emission (EMI)

- FCC Class A
- CE Class A
- C-Tick
- VCCI Class A
- BSMI Class A

Safety

- UL (UL1950)
- CSA (CSA950)
- TUV/GS (EN60950)



ACN 052 202 838



LISTED
ITE
E141136
66F9

Ordering Information

Ethernet/Fast Ethernet Switches

DES-1016R+ 16 10/100Mbps ports
DES-1024R+ 24 10/100Mbps ports

Optional Module

DES-102F 2 100Mbps Fast Ethernet fiber ports (SC connectors)

D-Link®

Specifications subject to change without prior notice.
D-Link is a registered trademark of D-Link Corporation/D-Link System Inc. All other trademarks belong to their proprietors.

U.S.A.
Canada
Europe
U.K.
Germany
France
Italy
Iberia
Sweden
Norway
Denmark
Finland
Singapore
Australia
Japan
China
India
Middle East
South America
South Africa
Russia
Taiwan
D-Link Corp.

TEL: 1-949-788-0805
TEL: 1-905-829-5033
TEL: 44-20-8731-5555
TEL: 44-20-8731-5555
TEL: 49-61-96779900
TEL: 33-1-30.23.86.88
TEL: 39-02-2900-0676
TEL: 34-93-4965751
TEL: 46-(0)8-564-61900
TEL: 47-22-991890
TEL: 45-43-96.90.40
TEL: 358-9-622-91660
TEL: 65-774-6233
TEL: 61-2-9417-7100
TEL: 81-3-5434-9678
TEL: 86-10-88097777
TEL: 91-22-652-6696
TEL: 202-2456176
TEL: 56-2-232-3185
TEL: 27(0)126652165
TEL: 7-095-737-3389
TEL: 886-2-2910-2626
TEL: 886-2-2916-1600

FAX: 1-949-753-7033
FAX: 1-905-829-5095
FAX: 44-20-8235-5511
FAX: 44-20-8235-5511
FAX: 49-61-967799300
FAX: 33-1-30.23.86.89
FAX: 39-02-2900-1723
FAX: 34-93-4965701
FAX: 46-(0)8-564-61901
FAX: 47-22-207039
FAX: 45-43-42.43.47
FAX: 358-9-622-91661
FAX: 65-774-6322
FAX: 61-2-9417-1077
FAX: 81-3-5434-9868
FAX: 86-10-88096789
FAX: 91-22-652-8914
FAX: 202-2456192
FAX: 56-2-232-0923
FAX: 27(0)126652186
FAX: 7-095-737-3390
FAX: 886-2-2910-1515
FAX: 886-2-2914-6299



RECYCLABLE
Rev. 01 (Mar. 2001)
Printed in Taiwan
7ES1016R+010