

Technical Accessory Guides (TAGs)

For Associates, Resellers, ISVs and Alliance Partners

Global



Version: All

Will show products that are known to be available for sale and discontinued products along with suggested replacements, when known

Need to provide an update or change?

Contact <mailto:ns9759@zebra.com>



For Internal Use by
PartnerConnect Members Only



DS8200 Technical Accessory Guide



NOTE: This document is only for general reference. Solutions Pathway and related PMBs should be used for product availability, pricing, and final solution selection.

* Zebra does not endorse or specifically recommend any **third-party products, accessories, or hardware**. ZEBRA DISCLAIMS ANY AND ALL LIABILITY, INCLUDING ANY EXPRESS OR IMPLIED WARRANTIES, WHETHER ORAL OR WRITTEN, FOR SUCH THIRD PARTY PRODUCTS, ACCESSORIES, OR HARDWARE. THE CUSTOMER ACKNOWLEDGES THAT NO REPRESENTATION HAS BEEN MADE BY ZEBRA AS TO THE FITNESS OF THE THIRD-PARTY PRODUCTS, ACCESSORIES, OR HARDWARE FOR THE CUSTOMER'S INTENDED PURPOSE.

Cradles (for DS8288)

Part Number	Picture	Description	Notes	Required Items
CR8288-SC100F4WW CR8288-SC100FBCN (for use in mainland China only)		Standard Charging/Communication Cradle - Black	► Provides radio and charging capabilities ► Cradle provides contactless, inductive charging to scanner ► Up to 8 scanners can be paired per cradle. ► USB-C port on bottom of cradle allows host pairing via right-angle USB-C to USB-C/A cable OR using standard MOD Jack. - USB-C connection allows for faster data throughput (e.g. use with image capture solutions) and faster charging (> 5V) when paired to appropriate host/charging devices. ► Certified at FIPS 140-3 ► Mounting hole pattern is backwards compatible with existing DS8178 mounting infrastructure.	Host communication cable and possibly a power supply depending on the host cable type.
CR8288-SC100FBWW CR8288-SC100FBCN (for use in mainland China only)		Standard Charging/Communication Cradle - Healthcare White	► Provides radio and charging capabilities ► Cradle provides contactless, inductive charging to scanner ► Up to 8 scanners can be paired per cradle. ► USB-C port on bottom of cradle allows host pairing via right-angle USB-C to USB-C/A cable OR using standard MOD Jack. - USB-C connection allows for faster data throughput (e.g. use with image capture solutions) and faster charging (> 5V) when paired to appropriate host/charging devices. ► Certified at FIPS 140-3 ► Mounting hole pattern is backwards compatible with existing DS8178 mounting infrastructure.	Host communication cable and possibly a power supply depending on the host cable type.
CR8288-PC100F4WW CR8288-PC100F4CN (for use in mainland China only)		Presentation Charging/Communication Cradle - Black	► Provides radio and charging capabilities ► Cradle provides contactless, inductive charging to scanner ► Up to 8 scanners can be paired per cradle. ► USB-C port on bottom of cradle allows host pairing via right-angle USB-C to USB-C/A cable OR using standard MOD Jack. - USB-C connection allows for faster data throughput (e.g. use with image capture solutions) and faster charging (> 5V) when paired to appropriate host/charging devices. ► Certified at FIPS 140-3 ► Mounting hole pattern is backwards compatible with existing DS8178 mounting infrastructure.	Host communication cable and possibly a power supply depending on the host cable type.

CR8288-PC100FBWW CR8288-PC100FBCN (for use in mainland China only)		Presentation Charging/Communication Cradle - Healthcare White	► Provides radio and charging capabilities ► Cradle provides contactless, inductive charging to scanner ► Up to 8 scanners can be paired per cradle. ► USB-C port on bottom of cradle allows host pairing via right-angle USB-C to USB-C/A cable OR using standard MOD Jack. - USB-C connection allows for faster data throughput (e.g. use with image capture solutions) and faster charging (> 5V) when paired to appropriate host/charging devices. ► Certified at FIPS 140-3 ► Mounting hole pattern is backwards compatible with existing DS8178 mounting infrastructure.	Host communication cable and possibly a power supply depending on the host cable type.
BT-RS5X6-DNGL-01		Bluetooth Adapter	► Allows 8288 series to be easily connected with hosts that do not have a Bluetooth radio for direct communication. ► Pairing barcode on adapter is scanned to instantly pair with the 8288 scanner. ► Up to 7 scanners can be paired per adapter. ► Paging button on adapter will trigger all paired scanners to beep, ideal for locating misplaced/hidden scanners. ► Adapter is powered from host via USB. ► Adapter can be easily mounted vertically or horizontally on tabletops, walls, poles, etc. using zip ties or screws (not included).	► USB Scanner Cable (CBA-U46-S07ZAR)
KT-RS5X6-BTDCBL-01		Bluetooth Adapter KIT	► Allows 8288 series to be easily connected with hosts that do not have a Bluetooth radio for direct communication. ► Pairing barcode on adapter is scanned to instantly pair with the 8288. ► Up to 7 scanners can be paired per adapter. ► Paging button on adapter will trigger all paired scanners to beep, ideal for locating misplaced/hidden scanners. ► Adapter is powered from host via USB. ► Adapter can be easily mounted vertically or horizontally on tabletops, walls, poles, etc. using zip ties or screws (not included). ► Kit includes: - Bluetooth Adapter (BT-RS5X6-DNGL-01) - USB Scanner Cable (CBA-U46-S07ZAR)	

Communication Cables

Standard USB Cables

Part Number	Picture	Description	Notes	Required Items
CBL-U67-S07ZAR		Shielded USB Cable: Right-Angle Series C to Series A Connector, 7ft. Straight	► Can be used simultaneously with MOD jack cable on Standard and Presentation cradles to assign charging duties to USB C cable ► Cradle-side USB connection designed for right-angle USB-C ► Charging rated for 7.5W (5V@1.5A) when paired with appropriate host/charger ► USB 3.2 Gen 1 allows for data transfer up to 5Gb/s	

CBL-U68-S07ZAR		Shielded USB Cable: Right-Angle Series C Connector, 7ft. Straight	► Can be used simultaneously with MOD jack cable on Standard and Presentation cradles to assign charging duties to USB C cable ► Cradle-side USB connection designed for right-angle USB-C ► Charging rated from 15W (5V@3A) to 60W (20V@3A) when paired with appropriate host/charger ► USB 3.2 Gen 1 allows for data transfer up to 5Gb/s	
CBA-U21-S07ZBR		USB Cable: Series A Connector, 7ft. Straight	► DS8100 series is NOT compatible with Rev A cable - CBA-U21-S07ZAR. Must use Rev B cable - CBA-U21-S07ZBR ► Will charge battery in 9 or 13 hours depending on the type of cradle used.	
CBA-U46-S07ZAR		Shielded USB Cable: Series A Connector, 7ft. Straight	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). CBA-U21-S07ZBR is typically used instead of this cable. ► Cable rated for 1.2A current ► If host provides 1.2A current, will charge battery in about 3 hours. Otherwise battery will charge in about 8.5 to 11.5 hours depending on type of cradle being used.	
CBA-U42-S07PAR		Shielded USB Cable: Series A Connector, 7ft. Straight - Powered	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). CBA-U21-S07ZBR is typically used instead of this cable. ► If using power from Host, will charge scanner in about 8.5 or 12 hours depending on type of cradle being used. ► External power supply will charge scanner battery in about 2.8 hours.	For faster charging use: ► 12V external Power Supply (PWR-BGA12V50W0WW) ► DC Line Cord (CBL-DC-375A1-01) ► AC Line Cord (23844-00-00R or country specific version)
CBA-U30-S15ZBR		USB Cable: Series A Connector, 15ft. Straight	► has heavier gauge wire vs. CBA-U30-S15ZAR, can support 5V and 12V power, scanner dependent	
CBA-U47-S15ZAR		Shielded USB Cable: Series A Connector, 15ft. Straight	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). CBA-U30-S15ZBR is typically used instead of this cable. ► Cable rated for 1.2A current ► If host provides 1.2A current, will charge battery in about 3 hours. Otherwise battery will charge in about 8.5 to 12 hours depending on type of cradle being used.	
CBA-U44-S15PAR		Shielded USB Cable: Series A Connector, 15ft. Straight - Powered	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). CBA-U30-S15ZBR is typically used instead of this cable. ► If using power from Host, will charge scanner in about 8.5 or 12 hours depending on type of cradle being used. ► External power supply will charge scanner battery in about 2.8 hours.	For faster charging use: ► 12V external Power Supply (PWR-BGA12V50W0WW) ► DC Line Cord (CBL-DC-375A1-01) ► AC Line Cord (23844-00-00R or country specific version)
CBA-U32-C09ZAR		USB Cable: (Series A Connector, 9ft. Coiled)		

CBA-U29-C15ZBR		USB Cable: Series A Connector, 15ft. Coiled	► has heavier gauge wire vs. CBA-U29-C15ZAR, can support 5V and 12V power, scanner dependent	
CBA-U65-S07ZAR		USB Cable: USB-C Connector, 7ft. Straight	► Cable is typically used with tablets and laptops with USB-C ports	
IBM POS USB Cables				
Part Number	Picture	Description	Notes	Required Items
CBA-U23-S07ZBR		USB Cable: Power Plus Connector, 7ft. Straight, 12V	► Has heavier gauge wire vs. CBA-U23-S07ZAR, can support 5V or 12V power, scanner dependent.	
CBA-U43-S07ZAR		USB Cable: Power Plus Connector, 7ft. Straight	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). CBA-U23-S07ZBR is typically used instead of this cable. ► Can support 5V or 12V power, scanner dependent.	
CBA-U35-S15ZBR		USB Cable: Power Plus Connector, 15ft. Straight	► Has heavier gauge wire vs. CBA-U35-S15ZAR, can support 5V or 12V power, scanner dependent	
CBA-U34-C09ZAR		USB Cable: Power Plus Connector, 9ft. Coiled		
CBA-U28-C15ZBR		USB Cable: Power Plus Connector, 15ft. Coiled	► Has heavier gauge wire vs. CBA-U28-C15ZAR, can support 5V and 12V power, scanner dependent.	
RS232 Cables				
Part Number	Picture	Description	Notes	Required Items
CBA-R01-S07PBR		RS232 Cable:STD-DB9 Female, TxD on 2, 7ft. Straight	► Includes improved TTL current limit protection circuitry vs. CBA-R01-S07PAR. ► Will charge battery in 4.5 to 5 hours depending on the type of cradle used.	Requires 5V external Power Supply (PWR-WUA5V4W0US or equivalent country specific model)
CBA-R07-S07PAR		RS232 Cable:STD-DB9 Female, TxD on 2, 7ft. Straight	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). ► Will charge battery in about 2.8 hours	Requires: ► 12V external Power Supply (PWR-BGA12V50W0WW) ► DC Line Cord (CBL-DC-375A1-01) ► AC Line Cord (23844-00-00R or country specific version)
CBA-R02-C09PAR		RS232 Cable:STD-DB9 Female, TxD on 2, 9ft. Coiled		Requires 5V external Power Supply (PWR-WUA5V4W0US or equivalent country specific model)
CBA-R71-C09ZAR		RS232 Cable:STD-DB9 Female, 9ft. Coiled, TxD on 2, PWR Pin 9	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). ► This cable is recommended for use with the VC80, VH10, 8585/8595, and 8515.	
CBA-R03-C12PAR		RS232 Cable:STD-DB9 Female, TxD on 2, 12ft. Coiled		Requires 5V external Power Supply (PWR-WUA5V4W0US or equivalent country specific model)

CBA-R37-C09ZBR		RS232 Cable: STD-DB9 Female, PWR Pin 9, 9ft coiled	► Includes improved TTL current limit protection vs. CBA-R37-C09ZAR.	
Siemens Nixdorf Beetle POS Terminal RS232 Cables				
Part Number	Picture	Description	Notes	Required Items
CBA-R08-S07ZBR		RS232 Cable: Nixdorf Beetle-5V Direct Power Cable 7ft. Straight	► Includes improved TTL current limit protection circuitry vs. CBA-R08-S07ZAR	
CBA-R09-C09ZAR		RS232 Cable: Nixdorf Beetle-5V Direct Power Cable 9ft. Coiled		
CBA-R10-S07ZBR		RS232 Cable: Nixdorf Beetle-12V Direct Power, 7ft. Straight	► Includes improved TTL current limit protection circuitry vs. CBA-R10-S07ZAR	
CBA-R13-S09EAR		RS232 Cable: Nixdorf Beetle-12V Direct Power, 7ft. Straight., with EAS	Integrates with Checkpoint EAS security tag system	
Other POS Terminal RS232 Cables				
Part Number	Picture	Description	Notes	Required Items
CBA-R24-C20ZAR		RS232 Cable: Fujitsu Team POS 500 ICL, 20ft Coiled		
CBA-R31-C09ZAR		CBL:RS232 (NCR7448) 9FT,CLD		
CBA-R47-C09ZAR		CBL:RS232 (NCR AUX PORT) 9FT, CLD		
25-32465-26		RS232 Cable: Datalogic Magellan scanner Auxiliary Port, 6ft Coiled	► Cable is compatible with DS8208. ► DS8208 is powered from the Magellan scanner.	
CBL-R64-C06PAR		RS232 Cable: Datalogic Magellan scanner Auxiliary Port, 6ft Coiled	► Cable is compatible with DS8288. ► Requires external power supply since Magellan scanner may not be able to provide enough power for DS8288.	Requires 5V external Power Supply (PWR-WUA5V4W0US or equivalent country specific model)
CBA-R28-C09ZAR		RS232 Cable: Verifone Ruby, 9ft, Coiled		

Keyboard Wedge Cables				
Part Number	Picture	Description	Notes	Required Items
CBA-K63-S07PAR		Keyboard Wedge Cable: PS/2, Power Port, 7ft. Straight - Powered	► This cable is typically used with 36XX series scanners but can also be used with CR8288 cradles (not DS8208). ► Host will provide enough power on PS2 port for Standard Charging/ Communication Cradle and will charge scanner in about 16.8 hours. - Zebra recommends using an external power supply to protect the host's PS2 port. ► External power supply is required when using with Presentation Charging/ Communication Cradle or if faster charging is needed when using Standard Charging/ Communication Cradle. Will charge scanner battery in about 2.8 hours. ► Supports host auto-detect so configuration barcode is not needed to put device into Keyboard Wedge mode.	Requires: ► 12V external Power Supply (PWR-BGA12V50W0WW) ► DC Line Cord (CBL-DC-375A1-01) ► AC Line Cord (23844-00-00R) under the following conditions: 1. if using Presentation Charging/Communication Cradle OR 2. If faster battery charging is needed when using Standard Charging/ Communication Cradle
IBM 468x/469x POS Cables				
Part Number	Picture	Description	Notes	Required Items
CBA-M61-S07ZAR		IBM 468x/9x, Port 9B Cable, 7ft. Straight	► Port 5B connection provides 5V power and will charge scanner in about 4 hours. ► Supports host auto-detect so configuration barcode is not needed to put device into IBM Host mode.	
CBA-M65-S07ZAR		IBM 468x/9x, Port 9B Cable, 7ft. Straight	► Port 9B connection provides 12V power and will charge scanner in about 3 hours. ► Supports host auto-detect so configuration barcode is not needed to put device into IBM Host mode.	
Scanner Emulation Cables (Not supported by DS82xx)				
Wand Cables (Not supported by DS82xx)				
Synapse Adapter Cables (Not supported by DS82xx)				
Terminal Specific Cables				
CBA-A51-S16ZAR		Auxiliary Scanner Cable to MP6000/MP7000, RS232 Serial	► Allows handheld scanners to be used with MP6000/MP7000 for scanning heavy/awkward items. ► 5 meter length ► RS232 serial connection to scanner ► Connects to AUX2 port on MP6000/MP7000 ► Provides power to corded scanners ► NOTE: MP6000/MP7000 supports maximum of 2 auxiliary scanners.	NOTE: If cradle is used with a cordless scanner, it must be powered using an external power supply.
Misc				
Part Number	Picture	Description	Notes	Required Items
STND-GS0082C-04		Gooseneck Intellistand - Black	► Stand is compatible with DS8208, DS8208-R ► Not compatible with DS8288, DS8288-R	

STND-WS0082C-04		Weighted Gooseneck Intellistand - Black	► Stand features a weighted base. ► Stand is compatible with DS8208, DS8208-R ► Not compatible with DS8288, DS8288-R	
CUP-GS0082C-04		Gooseneck Cup - Black	► Allows scanner to be mounted in a fixture or other equipment. ► Not compatible with DS8288, DS8288-R	
STND-GS0082C-0B		Gooseneck Intellistand - Healthcare White	► Typically used with Healthcare (HC) versions of scanner. ► Stand is compatible with DS8208-HC. ► Not compatible with DS8288-HC.	
STND-WS0082C-0B		Weighted Gooseneck Intellistand - Healthcare White	► Stand features a weighted base. ► Typically used with Healthcare (HC) versions of scanner. ► Stand is compatible with DS8208-HC. ► Not compatible with DS8288-HC.	
CUP-GS0082C-0B		Gooseneck Cup - Healthcare White	► Allows scanner to be mounted in a fixture or other equipment. ► Not compatible with DS8288, DS8288-R	

BRKT-AP0081W-04		4278-6878 series Cradle Adapter Bracket	► Allows DS8288 Standard Charging/Communication Cradle (CR8288-SC) to be used with fixtures designed to hold the 4278-6878 Standard Charging/Communication Cradle (CR0078-SC). ► Hole pattern on Adapter Bracket matches hole pattern on 4278-6878 Cradle. DS8288 Cradle then attaches to bracket. ► Adapter Bracket can also be attached to the 4278-6878 Wall Mount Bracket for CR0078-SC and CR0008-SC Cradles (21-135001-01). The spacers on the Wall Mount bracket will need to be removed to attach the two brackets together.	
FAST-PC0081W-Q1 (one set of 4)		Adhesive Fastening Straps for Cradles	► Set of four adhesive backed hook fastening strips used to adhere one CR8288-SC or CR8288-PC charging communication cradle to a surface. ► Allows easy insertion and removal of scanner from the cradle.	
215994 (3rd party) * https://www.proclipusa.com		ProClip Mounting Plate for Standard Cradle	► Mounting plate keeps the scanner within easy reach. ► Uses AMPS hole pattern for easy mounting. ► Can be attached to a ProClip pedestal or any flat surface.	
216040 (3rd party) * https://www.proclipusa.com		ProClip Mounting Plate with Quick Release Speed Clip for Presentation Cradle	► Mounting plate keeps the scanner within easy reach. ► Uses AMPS hole pattern for easy mounting. ► Can be attached to a ProClip pedestal or any flat surface. ► ProClip 45mm non-charging Quick Release Speed Clip allows easy removal of cradle, when needed.	
Power Supplies/Power Cords				
Part Number	Picture	Description	Notes	Required Items
CBL-DC-375A1-01		DC Power Cord	► Used along with Power Supply PWR-BGA12V50W0WW. ► Cable length is 1.5 meters	

PWR-BGA12V50W0WW		Power Supply	► 100-240 VAC, 12V, 4.16A, 50W ► Provides US DOE Level VI compliance for power efficiency. ► Replaces PWRS-14000-148R	► DC Line Cord (CBL-DC-375A1-01) ► AC Line Cord (23844-00-00R or country specific version)
PWR-WUA5V12W0US (US plug style) PWR-WUA5V12W0GB (UK plug style) PWR-WUA5V12W0EU (EU plug style) PWR-WUA5V12W0AU (Australia plug style) PWR-WUA5V12W0CN (China plug style) PWR-WUA5V12W0IN (India plug style) PWR-WUA5V12W0KR (Korea plug style) PWR-WUA5V12W0BR (Brazil plug style) PWR-WUA5V12W0LA (Argentina/Chile/Mexico plug styles)		USB-A Power Supply	► 100-240 VAC, 5 V, 2.5 A, 12W output	
PWR-WUA5V45W1US (US plug style) PWR-WUA5V45W1GB (UK plug style) PWR-WUA5V45W1EU (EU plug style) PWR-WUA5V45W1AU (Australia plug style) PWR-WUA5V45W1CN (China plug style) PWR-WUA5V45W1IN (India plug style) PWR-WUA5V45W1KR (Korea plug style) PWR-WUA5V45W1BR (Brazil plug style) PWR-WUA5V45W1AR (Argentina/Chile/Mexico plug styles)		USB-C Power Supply	► Provides up to 45W power for faster charging ► 100-240 VAC	
PWR-WUA5V6W0WW		USB Power Supply	► Can be used to power cradles to create a "charge-only" cradle solution for customers wanting to pair DS8288 directly to host. ► Includes four international plugs for use in US, UK, EU, and AU. Additional plugs can be purchased separately for other countries. ► 5.2V, 1.2A, 6W output ► Provides US DOE Level VI compliance for power efficiency	Standard or Presentation Cradle AND USB Cable (CBA-U21-S07ZBR)
PWR-WUA5V6W0WHT		USB Power Supply, White color	► To be discontinued 5/2026 - see PMB-11754 ► Can be used to power cradles to create a "charge-only" cradle solution for customers wanting to pair DS8288 directly to host. ► Includes four international plugs for use in US, UK, EU, and AU. Additional plugs can be purchased separately for other countries. ► 5.2V, 1.2A, 6W output ► Provides US DOE Level VI compliance for power efficiency ► NOTE: SKU is restricted sale. May require Zebra Product Management approval to order.	Standard or Presentation Cradle AND USB Cable (CBA-U21-S07ZBR)
CN-000803-01		<u>Spare/Replacement</u> USB Power Supply AC Clip for Australia (AUS)	► This AC Clip is normally included with PWR-WUA5V6W0WW ► 2 pin Australia plug	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-02		USB Power Supply AC Clip for Argentina (ARG)		USB Power Supply (PWR-WUA5V6W0WW)

CN-000803-03		USB Power Supply AC Clip for Korea (KOR)		USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-04		<u>Spare/Replacement</u> USB Power Supply AC Clip for US (US)	► This AC Clip is normally included with PWR-WUA5V6W0WW ► 2 pin US plug	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-05		<u>Spare/Replacement</u> USB Power Supply AC Clip for Europe (EU)	► This AC Clip is normally included with PWR-WUA5V6W0WW	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-06		<u>Spare/Replacement</u> USB Power Supply AC Clip for UK (UK)	► This AC Clip is normally included with PWR-WUA5V6W0WW	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-07		USB Power Supply AC Clip for China (CHN)	► straight pins China plug	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-08		USB Power Supply AC Clip for Brazil (BRA)	► 2 pin Brazil plug	USB Power Supply (PWR-WUA5V6W0WW)
CN-000803-09		USB Power Supply AC Clip for India (IND)		USB Power Supply (PWR-WUA5V6W0WW)
PWR-WUA5V4W0US		Power Supply (US)	► Used when connecting communication cables labeled above as "Requires external power supply". ► For use in US, CA, MX, JP, TW. ► 5.2V, 1.1A, 5.7W ► Provides US DOE Level VI compliance for power efficiency. ► Replaces PWRS-14000-253R	
PWR-WUA5V4W0IN		Power Supply (India)	► Used when connecting communication cables labeled above as "Requires external power supply". ► For use in India. ► 5.2V, 1.1A, 5.7W ► Provides US DOE Level VI compliance for power efficiency. ► Replaces PWRS-14000-254R	
PWR-WUA5V4W04C		Power Supply (EU, UK, Brazil, Australia, China)	► Used when connecting communication cables labeled above as "Requires external power supply". ► Includes AC adapter clips for use in EU, UK, Brazil, Australia and China. ► 5.2V, 1.1A, 5.7W ► Provides US DOE Level VI compliance for power efficiency.	
PWR-WUA5V4W0EU		Power Supply (EU and UK)	► Used when connecting communication cables labeled above as "Requires external power supply". ► For use in EU and UK. ► 5.2V, 1.1A, 5.7W ► Provides US DOE Level VI compliance for power efficiency. ► Replaces PWRS-14000-256R	
23844-00-00R		AC Line Cord	► This AC Line Cord is for use in North America. See the AC Line Cords by Country TAG for comparable line cords to use in other countries.	

Batteries				
Part Number	Picture	Description	Notes	Required Items
BTRY-DS82EAB0E-00 BTRY-DS82EAB0E-00Y (India only)		DS8288 Spare Battery with PowerPrecision+ (3500 mAh) 	► Designed, manufactured & tested to meet rigorous controls & standards ► Premium-grade cells with higher capacity & longer life cycle ► Designed to help prevent overcharging & electrical shock ► Information available: - Battery Asset Information + Manufacture Date of Battery + Serial Number of Battery + Model Number of Battery + Firmware Version of Battery + Design Capacity - Battery Life Statistics + State of Health Meter + Charge Cycles Consumed - Battery Status (at Time of Poll) + State of Charge + Remaining Capacity + Charge Status + Remaining Time to Complete Charging + Battery Voltage / Current - Battery Temperature + Present/Highest/Lowest	
SUPR-DS82EAB0E-00		DS8288 PowerCapTM	► Super capacitor can be used in lieu of standard PowerPrecision+ battery in any DS8288 device. ► Can provide up to 6000 scans when fully charged; capable of ultra-fast charging from empty to 100 scans in 35 seconds ► PowerCap can be charged in 60 minutes over standard USB, 15 minutes over BC1.2 USB, 13 minutes over external 5V source, 13 minutes over external 12V source, and 14 minutes over USB Type C ► Green label and visible stripe distinguish PowerCap from standard battery.	